

## What's New in C15 Software Version 21-49 (vs. 21-33)

### MIDI Settings:

- The layout and some of the labels of the MIDI Settings have been revised.
- In the new "Channels" section the MIDI Channels for both Send and Receive can be set.
- The "Mappings" section has been renamed to "Assignments".
- The "Set to Defaults" entries have been moved to the "Assignments" section.
- The new "Routings" section contains a matrix editor that determines for Notes, Program Changes and each of the 8 Hardware Sources separately, if MIDI messages are sent or received via the Primary MIDI channel or the Split channel. In the matrix you can also enable and disable the "Local" connections between the elements of the C15's play interface and the C15's sound engine.
- There is a global "Local Enable" in the second line of the MIDI Settings. When it is set to "Off" the Local connections of all elements are interrupted.
- The "Panic" entry has been moved to the first line.
- The former "Receive", "Send" and "Local" sections have been removed in favor of the new approach.
- Correct display of CC numbers for 7-bit and 14-bit resolution in the Assignments and in the Ribbon labels.

### "Local Off" for Ribbons:

If a Ribbon is set to "Local Off" the display of the base unit shows the MIDI CC that is assigned. The Ribbon LEDs show the position that is sent via MIDI.

### MIDI Program Change Bank:

Selecting a Preset in the PC Bank will send a Program Change message also when the bank is not selected (Direct Load = Off).

### All Notes Off, Internal Voice Reset:

More consistent behaviour when resetting the internal voices and sending a "All Notes Off" message via MIDI. This is used to avoid stuck notes when the MIDI routings or Local connections are changed.

## **Panic Function on Buttons:**

Pressing all four buttons of the base unit ("-", "+", "Funct", "Mode") at the same time will reset all internal voices and send "All Notes Off" via MIDI.

## **WiFi Passphrase:**

The passphrase can now be edited and reset to the default (88888888). A "Randomize" ("Dice") function is still available, too.

## **Fixes and Improvements:**

- in some Preset Store functions
- in the Backup Restore function
- in the New Bank function
- in the Bank Collapse function
- in the Bank Import function
- in the Preset screen
- in the Preset/Bank file format to fix a problem with Split Sound parameters

**!** Please note: The Bank and Backup files stored with this software version cannot be loaded with earlier versions.

## **Known Issues:**

- When Local is disabled, not every necessary "All Notes Off" message is sent to stop stuck notes.
- The button combination for "Panic" can lead to unintended changes on the base unit settings.

## **Manual:**

You find an updated Studio Package Addendum (v19) on the "Manuals" page of our website.